

# MANUAL ATCOM AG-168



# Untuk mengetahui IP

- Untuk mengetahui IP, tekan tombol **IP** yang ada pada **ATCOM AG-168** dan dengarkan keterangannya di telepon

# Konfigurasi Account

- Buka Internet Explorer / Web browser lainnya
- Masukan IP address dari IP Phone yang baru kita Setting



# TAMPILAN UTAMA

Network Settings					
iptype	static	ppp id		ppp pin	
local ip	172.19.51.4	subnet mask	255.255.255.224	router ip	172.19.51.1
dns	219.83.41.158	dns2	219.83.41.157	mac	00-09-45-63-bb-c8
Audio Settings					
codec1	g729	codec2	g7231	codec3	gsm
codec4	iLBC	codec5	g711u	codec6	g711a
vad	<input type="checkbox"/>	agc	<input checked="" type="checkbox"/>	aec	<input checked="" type="checkbox"/>
audio frames	2	jitter size	0	g.723.1 high rate	<input checked="" type="checkbox"/>
Phone Settings					
use dialplan	disable	dial number		ddd code	10
idd code	86	idd prefix	00	ddd prefix	0
inner line	disable	inner line prefix	0	call waiting	<input type="checkbox"/>
forward number	82378009	fwd poweroff	<input type="checkbox"/>	fwd noanswer	<input type="checkbox"/>
fwd always	<input type="checkbox"/>	fwd busy	<input type="checkbox"/>	answer	30
use digitmap	<input type="checkbox"/>	handset in(0-15)	7	handset out(0-31)	27
dual mode	ip first	dual mode prefix	99		
SIP Protocol Settings					
use service	<input checked="" type="checkbox"/>	register ttl	60		
service type	common	sip proxy	voiprakyat.or.id	domain/realm	voiprakyat.or.id
nat traversal	stun	nat addr	voiprakyat.or.id	nat ttl	30
phone number	27325	account	27325	pin	abc7182
register port	5060	rtp port	8000	rtp tos	0
call type	advanced	dtmf	rfc2833	dtmf payload	101
super password	12345678	debug	no check		
Other Settings					
password	1234	upgrade type	disable	upgrade addr	
sntp ip	0.0.0.0	use daylight	<input type="checkbox"/>		
timezone	(GMT+07:00)Bangkok,Jakarta,Hanoi				
Save Settings		Address Book		Upgrade Firmware	

# NETWORK SETTINGS

- IPtype : static
- Local IP : Misal 172.19.51.4
- Subnet mask : Misal 255.255.255.224
- Router IP : Misal 172.19.51.1
- Dns : Misal 219.83.41.158
- Dns2 : Misal 219.83.41.157

Network Settings					
iptype	static ▼	ppp id		ppp pin	
local ip	172.19.51.4	subnet mask	255.255.255.224	router ip	172.19.51.1
dns	219.83.41.158	dns2	219.83.41.157	mac	00-09-45-63-bb-c8

# AUDIO SETTINGS

- Codec1 : Misal g729
- Codec2 : Misal g7231
- Codec3 : Misal gsm
- Codec4 : Misal iLBC
- Codec5 : Misal g711u
- Codec6 : Misal g711a

Audio Settings					
codec1	<input type="text" value="g729"/>	codec2	<input type="text" value="g7231"/>	codec3	<input type="text" value="gsm"/>
codec4	<input type="text" value="iLBC"/>	codec5	<input type="text" value="g711u"/>	codec6	<input type="text" value="g711a"/>
vad	<input type="checkbox"/>	agc	<input checked="" type="checkbox"/>	aec	<input checked="" type="checkbox"/>
audio frames	<input type="text" value="2"/>	jitter size	<input type="text" value="0"/>	g.723.1 high rate	<input checked="" type="checkbox"/>

# SIP PROTOCOL SETTINGS

- Use service : Diberi checkbox
  - Service type : common
  - Sip proxy : voiprakyat.or.id
  - Domain/realm : voiprakyat.or.id
  - Nat traversal : stun
  - Nat addr : voiprakyat.or.id
- Phone number : Misal 27325  
Pin : Misal abc7182  
Register port : 5060  
Rtp port : 8000

SIP Protocol Settings					
use service	<input checked="" type="checkbox"/>	register ttl	<input type="text" value="60"/>		
service type	<input type="text" value="common"/>	sip proxy	<input type="text" value="voiprakyat.or.id"/>	domain/realm	<input type="text" value="voiprakyat.or.id"/>
nat traversal	<input type="text" value="stun"/>	nat addr	<input type="text" value="voiprakyat.or.id"/>	nat ttl	<input type="text" value="30"/>
phone number	<input type="text" value="27325"/>	account	<input type="text" value="27325"/>	pin	<input type="text" value="abc7182"/>
register port	<input type="text" value="5060"/>	rtp port	<input type="text" value="8000"/>	rtp tos	<input type="text" value="0"/>
call type	<input type="text" value="advanced"/>	dtmf	<input type="text" value="rfc2833"/>	dtmf payload	<input type="text" value="101"/>
super password	<input type="text" value="12345678"/>	debug	<input type="text" value="no check"/>		

# OTHER SETTINGS

- Password : Misal 1234
- Upgrade type : disable
- Time Zone : (GMT + 07:00)Bangkok,Hanoi,Jakarta

- Jika setelah semuanya diisi Klik Save Settings → 

Other Settings			
password	<input type="text" value="1234"/>	upgrade type	<input type="text" value="disable"/>
sntp ip	<input type="text" value="0.0.0.0"/>	use daylight	<input type="checkbox"/>
timezone	<input type="text" value="(GMT+07:00)Bangkok,Jakarta,Hanoi"/>		
<input type="button" value="Save Settings"/>		<input type="button" value="Address Book"/>	<input type="button" value="Upgrade Firmware"/>



# Terima kasih dan selamat mencoba

## KONTAK

Jakarta Centre of ICT Studies

<http://www.ictcentre.net>

Jl. Pangkalan Jati II No.B1 Jakarta  
Timur

DKI Jakarta Indonesia 13620

Landline: +62 21 8613027

Fax: +62 21 8618952

VR: 0809 88 ICT

# Penulis

Wina Februarita  
SMK Negeri 1 Rangkasbitung  
[wina\\_06@yahoo.com](mailto:wina_06@yahoo.com)

# Editor

Rini Hariyani  
[Riniers\\_03@yahoo.com](mailto:Riniers_03@yahoo.com)

Anton Raharja  
[anton@ngoprek.org](mailto:anton@ngoprek.org)