



Membuat Server VoIP Dengan TRIKBOX



Instalasi

- Lakukan Instalasi Terlebih System Operasi TRIXBOX terlebih dahulu
- Instalasi dilakukan sama dengan Instalasi pada System Operasi Linux lainnya
- Hardisk Anda akan ter-format otomatis oleh Linux TRIXBOX ini

Catatan :


Backup data anda sebelum instalasi dilakukan



Konfigurasi IP TRIXBOX

- Setelah Instalasi, Anda harus mengkonfigurasi IP Address dengan cara :
 - Ketik netconfig ↵
 - Pilih Yes ↵
 - Isi IP Address, Netmask, Default Gateway (IP) dan Primary Name server
 - Pilih OK ↵
 - Kemudian Ketik **/etc/init.d/network restart** dan **enter** untuk me-restart network

Konfigurasi TRIXBOX



- Masuk ke Internet Explorer / Web Browser lainnya
- Ketik IP Address **TRIXBOX** (Misal 172.19.51.5)

Tampilan Awal Konfigurasi TRIKBOX

The screenshot shows a Microsoft Internet Explorer browser window displaying the TriXbox configuration page. The browser's address bar shows the URL `http://172.19.51.5/`. The page features the TriXbox logo at the top left, a navigation menu on the left, and a main content area with a date and time stamp. The footer contains the copyright information for 2006.

trixbox - up and running in one hour - Microsoft Internet Explorer

File Edit View Favorites Tools Help

Back Forward Stop Home Search Favorites Refresh Print Mail Stop Yahoo! Messenger

Address `http://172.19.51.5/`

Search Web Search Mail My Yahoo! Answers Games Local ML

trixbox - up and running in one ... + Add Tab

trixbox

[ABOUT](#)

Version: 1.1.0 July 13, 2006 | 10:18:54

- ▶ Asterisk
 - ▶ Voicemail & Recordings
 - ▶ Web MeetMe Control
 - ▶ Flash Operator Panel
 - ▶ System Administration
- ▶ Applications
 - ▶ Sugar CRM

Copyright © 2006 by trixbox.org



ABOUT

Version: 1.1.0

July 13, 2006 | 10:55:56

▶ Asterisk

▶ Voicemail & Recordings

▶ Web MeetMe Control

▶ Flash Operator Panel

▶ [System Administration](#) ←

▶ Applications

▶ Sugar CRM

Copyright © 2006 by trixbox.org

- Klik **System Administration** Untuk masuk ke menu System administration

The Trixbox logo features the word "trixbox" in a bold, lowercase, sans-serif font. The letter "i" is stylized with a small orange asterisk above it. The "x" is composed of two blue shapes that resemble the letter "x" with a white outline.


Version: 1.1.0

▶ Asterisk

- ▶ Voicemail & Recordings
- ▶ Web MeetMe Control
- ▶ Flash Operator Panel
- ▶ System Administration

▶ Applications

- ▶ Sugar CRM

A Windows-style dialog box titled "Connect to 172.19.51.5" with a blue header bar containing a key icon. The main area is labeled "Restricted Area" and contains a "User name:" field with a dropdown menu showing "maint", a "Password:" field with masked characters, and a checkbox for "Remember my password". "OK" and "Cancel" buttons are at the bottom.

Connect to 172.19.51.5

Restricted Area

User name: maint

Password:

Remember my password

OK Cancel


ABOUT

July 13, 2006 | 10:58:37


Copyright © 2006 by trixbox.org

- Isi user dengan **maint**
- Isi Password dengan **password**
- Klik **OK** untuk melanjutkan

Menu System Administration



The screenshot displays the trixbox Configuration and Administration web interface. At the top left is the trixbox logo, and at the top right is the text "Configuration and Administration" next to a gear icon. A dark blue navigation bar contains "MAIN" and "ABOUT" links. Below this, the version "1.1.0" and the date/time "July 13, 2006 | 11:09:29" are shown. A left sidebar lists menu items under "Asterisk" and "System". The main content area, titled "Main Menu", displays "Welcome to trixbox".

trixbox Configuration and Administration 

MAIN ABOUT

Version: 1.1.0 July 13, 2006 | 11:09:29

- ▶ **Asterisk**
 - ▶ FreePBX
 - ▶ Config Edit
 - ▶ Asterisk Info
 - ▶ Endpoint Manager
 - ▶ HUD Manager
- ▶ **System**
 - ▶ phpMyAdmin
 - ▶ System Info
 - ▶ System Maint
 - ▶ SSH Terminal
 - ▶ Munin

Main Menu

Welcome to trixbox



Version: 1.1.0

July 13, 2006 | 11:24:35

- ▶ Asterisk
 - ▶ **FreePBX** ←
 - ▶ Config Edit
 - ▶ Asterisk Info
 - ▶ Endpoint Manager
 - ▶ HUD Manager
- ▶ System
 - ▶ phpMyAdmin
 - ▶ System Info
 - ▶ System Maint
 - ▶ SSH Terminal
 - ▶ Munin

Main Menu

Welcome to trixbox

- Klik Menu **FreePBX** untuk masuk ke Menu **FreePBX**

Menu FreePBX



The screenshot displays the FreePBX Administration interface. At the top left is the FreePBX logo. A navigation menu at the top right includes links for Setup, Tools, Reports, Panel, and Recordings. Below the logo, a 'Welcome' button is visible. On the right side, there is a 'Language' dropdown menu currently set to 'English'. The main content area features the FreePBX logo and a welcome message: 'Welcome to the FreePBX Administration 2.1.1'.

freePBX™

• Setup • Tools • Reports • Panel • Recordings

Administration

Welcome

Language: English

freePBX

Welcome to the FreePBX Administration 2.1.1



freePBX™

• Setup • Tools • Reports • Panel • Recordings

Administration

Welcome

Language: English

freePBX

Welcome to the FreePBX Administration 2.1.1

- Klik Menu **Tools**
- Pertama kali kita harus melakukan instalasi module: Core




Menu Tools

freePBX™ [• Setup](#) [• Tools](#) [• Reports](#) [• Panel](#) [• Recordings](#)

Tools

Module Admin

freePBX™ Version 2.1.1 on 172.19.51.5



freePBX™

• Setup • Tools • Reports • Panel • Recordings

Tools

Module Admin

- **Klik Module Admin**



Module Admin

Module Administration

[Connect to Online Module Repository](#)

Not Installed Local Modules

	Module	Version	Type	Category
<input type="checkbox"/>	Asterisk API (manager)	1.0.2	tool	Basic
<input checked="" type="checkbox"/>	Core (core)	1.1	setup	Basic
<input type="checkbox"/>	Feature Code Admin (featurecodeadmin)	1.0	setup	Basic
<input type="checkbox"/>	Follow Me (findmefollow)	1.2.5	setup	Basic
<input type="checkbox"/>	Ring Groups (ringgroups)	1.2.2	setup	Basic
<input type="checkbox"/>	Time Conditions (timeconditions)	2.1	setup	Basic
<input type="checkbox"/>	Call Forward (callforward)	1.0.2	setup	Call Management
<input type="checkbox"/>	Call Waiting (callwaiting)	1.0.1	setup	Call Management
<input type="checkbox"/>	Do-Not-Disturb (DND) (donotdisturb)	1.0.1	setup	Call Management
<input type="checkbox"/>	VoicePulse (voicepulse)	0.1	setup	ITSP
<input type="checkbox"/>	Voicemail (voicemail)	1.0	setup	Messaging

- Beri Tanda pada **Core (core)**

Enable Selected

- Pilih **Enable Selected** dan kemudian **Submit**



Module Admin

Module Administration

[Connect to Online Module Repository](#)

Enabled Modules

<input type="checkbox"/>	Module	Version	Type	Category
<input type="checkbox"/>	Core (core)	1.1	setup	Basic

Disable Selected

- Klik Menu **Setup**

Menu Setup

freePBX™

• Setup • Tools • Reports • Panel • Recordings

Setup

Administrators

Extensions

General Settings

Inbound Routes

Outbound Routes


Trunks

freePBX™

Version 2.1.1 on 172.19.51.5



- Klik Menu **Extensions**



Administrators
Extensions
General Settings
Inbound Routes
Outbound Routes
Trunks

- Pada Menu **Add an Extensions**

Klik Menu **SIP**

Administrators	<h2>Add an Extension</h2> <p>Select device technology:</p> <ul style="list-style-type: none">• SIP ←• IAX2• ZAP• Custom
Extensions	
General Settings	
Inbound Routes	
Outbound Routes	
Trunks	

Menu Add SIP Extensions

		Setup
<p>Administrators</p> <p>Extensions</p> <p>General Settings</p> <p>Inbound Routes</p> <p>Outbound Routes</p> <p>Trunks</p>	<h2>Add SIP Extension</h2> <p style="text-align: right;">Add Extension</p> <hr/> <p>Add Extension</p> <hr/> <p><u>Extension Number</u>: <input type="text"/></p> <p><u>Display Name</u>: <input type="text"/></p> <p>Extension Options</p> <hr/> <p><u>Direct DID</u>: <input type="text"/></p> <p><u>DID Alert Info</u>: <input type="text"/></p> <p><u>Outbound CID</u>: <input type="text"/></p> <p><u>Emergency CID</u>: <input type="text"/></p> <p><u>Record Incoming</u>: <input type="text" value="On Demand"/></p> <p><u>Record Outgoing</u>: <input type="text" value="On Demand"/></p> <p>Device Options</p> <hr/> <p>secret <input type="text"/></p> <p>dtmfmode <input type="text" value="rfc2833"/></p> <p>Voicemail & Directory: <input type="text" value="Disabled"/></p>	

Add Extension

Extension Number:

Display Name:

Extension Options

Direct DID:

DID Alert Info:

Outbound CID:

Emergency CID:

Record Incoming:

Record Outgoing:

Device Options

secret

dtmfmode

- Isi Extensions Number : Misal **101**


- Isi Display Name : Misal **line1**

- Isi Secret : Misal **123456**

- Kemudian Klik Submit 

- **Add SIP Extensions** digunakan untuk membuat/menambahkan Client.

- **Extensions** = User/No VoIP
- **secret** = Password



You have made changes - when finished, click here to APPLY them

treePBX


• Setup • Tools • Reports • Panel • Recordings

Setup


Administrators	<h2>Add SIP Extension</h2> <p>Add Extension</p> <hr/> <p>Extension Number: <input type="text"/></p> <p>Display Name: <input type="text"/></p>	Add Extension
Extensions		line1 <101>
General Settings		
Inbound Routes		
Outbound Routes		
Trunks		

- Klik **You have made changes-when finished, click here to APPLY them**
Untuk menyimpan hasil perubahan.

- Klik Menu Trunks



- Klik Menu Add SIP Trunk



- Trunk Name : Isikan **voiprakyat.or.id**
- Host = **Voiprakyat.or.id**
- username = voiprakyat.or.id
- Secret= **Password**
- Register String :
(Username : password@voiprakyat.or.id)
- Klik **Submit Changes** untuk menyelesaikan konfigurasi

Outgoing Settings

Trunk Name:

PEER Details:

```
host=voiprakyat.or.id
username=25627
secret=abc5484
type=peer
```

Incoming Settings

USER Context:

USER Details:

```
secret=***password***
type=user
context=from-trunk
```

Registration

Register String:



You have made changes - when finished, click here to APPLY them

treePBX


• Setup • Tools • Reports • Panel • Recordings

Setup

Administrators	<h2>Edit SIP Trunk</h2> <p>Delete Trunk voiprakyat.or.id</p> <p>In use by 2 routes</p> <h3>General Settings</h3> <p><u>Outbound Caller ID:</u> <input type="text"/></p> <p><u>Maximum channels:</u> <input type="text"/></p>	Add Trunk
Extensions		Trunk ZAP/g0
General Settings		Trunk SIP/voiprakyat.
Inbound Routes		
Outbound Routes		
Trunks		


- Klik **You have made changes-when finished, click here to APPLY them**
Untuk menyimpan hasil perubahan.

- Klik **Outbound Routes**



A vertical navigation menu with the following items: Administrators, Extensions, General Settings, Inbound Routes, Outbound Routes (highlighted in orange), and Trunks.

- Route Name: Isikan **voiprakyat.or.id**
- Dial Patterns Isi misal **6|x.**
- Trunk Squence Pilih **SIP/voiprakyat.or.id**
- Klik **Add** untuk menambahkan Outbound Routes



Add Route

Route Name:

Route Password:

Emergency Dialing:

Dial Patterns

Insert:

Trunk Sequence



You have made changes - when finished, click here to APPLY them

treePBX

• Setup • Tools • Reports • Panel • Recordings

Setup

Administrators	<h2>Add Route</h2> <p>Route Name: <input type="text"/></p> <p>Route Password: <input type="text"/></p> <p>Emergency Dialing: <input type="checkbox"/></p> <p>Dial Patterns</p>	Add Route
Extensions		0 9_outside
General Settings		↩
Inbound Routes		1 voiprakyat.or.id
Outbound Routes		↩
Trunks		

- Klik **You have made changes-when finished, click here to APPLY them**
Untuk menyimpan hasil perubahan.



KETERANGAN

- Extensions
 - Merupakan data account extensions (atau client)
- Trunks
 - Merupakan data account trunks (atau server lain)
- Outbound Routes
 - Merupakan aturan dial yang akan dimanfaatkan oleh extensions untuk menghubungi trunks



Terima Kasih Dan Selamat Mencoba

KONTAK

Jakarta Centre of ICT Studies

<http://www.ictcentre.net>

Jl. Pangkalan Jati II No.B1 Jakarta Timur

DKI Jakarta Indonesia 13620

Landline: +62 21 8613027

Fax: +62 21 8618952

VR: 0809 88 ICT



Penulis

Roni Rodika
SMK Negeri 1 Tangerang
funkeyz4@telkom.net

Editor

Rini Hariyani
Riniers_03@yahoo.com

Anton Raharja
anton@ngoprek.org